

# powerbass:::



BT-200 SPLIT


**User's Manual** 

# Step 1 - Power On **Bluetooth Connection**




Long-press 'MASTER' and 'SUB-MASTER' (v) simultaneously for 2 seconds, you will hear prompt tone of power on. and they will begin to connect automatically. An audible beep will sound when connected successfully. The indicator light of SUB-MASTER will remain blue, and master indicator light flashes quickly.

Step 2 - Phone **Bluetooth Choose Device** 




Find "BT-200" in your bluetooth list and select lt.

Step 3 - Pairing Success **Bluetooth Indicator** 



The LED Indicator remains blue once pairing is done, music may be played afterwards.

**TWS Function** 




(Master and Sub-master shown above)

Long press MASTER and SUB-MASTER ( simultaneously for two seconds, you will hear a prompt tone of power on, and they will begin to connect automatically.

(Please turn on bluetooth on your device before TWS pairing)

# **Basic Operation**




(a) POWER BUTTON/MULTI-FUNCTION BUTTON Power on/off: Long Press (U) for 2 seconds Answer/end call: Short Press (U) on MASTER speaker Reject call: Press (4) twice on MASTER speaker Resume/pause music: Short Press (4) Disconnect TWS and Bluetooth: Press (4) 3x to disconnect TWS, then 2x to disconnect bluetooth device.

(+) (-) VOLUME BUTTONS Volume increase: Short press (+) Volume decrease: Short press (-) Next track: Long press (+) Previous track: Long press (-)

NOTE: Both speakers are mutually controlled after pairing.

## Interface Instructions

2



# SWITCH INDICATOR

. Blue LEO flashes quickly when turning on speaker . Blue LED flashes quickly when the speakers are pairing

#### BLUETOOTH INDICATOR

- . Blue LED will remain on after successful connection.
- . The LED light of the SUB-MASTER will remain on, while the MASTER will flash quickly after successful pairing.
- The Blue LED flashes quickly if the speakers are beyond range of the Bluetooth source (Unit will power off automatically if no connection is made after 10 minutes)

## CHARGING INDICATOR

- Red LED indicator will remain illuminated while charging.
- · Red LED indicator will turn off after a full charge.
- · Red LED indicator will flash when the battery is low.
- . The LED Indicator will turn off when powered off.

## **BT-200 Specifications**

3

Product Name: BT-200 SPLIT

Bluetooth Version: 5.0

Battery Capacity: 1500mAh x 2

Play Time: 10-12 hours

Charging Time: 3~4 hours

Driver Units: 10W x 2

Charging Current: 5V / 0.8A

Product Dimensions: 84 x 84 x 210mm

Product Weight: 750g

### NOTES:

- 1. Please read this manual carefully before use.
- 2. Upon using the speaker for the first time, please fully charge the unit.
- 3. Please use the included certified adapter which has passed national safety certifications.
- 4. Please charge the speaker at least once a month to maintain battery performance.
- 5. Using this speaker in extremely cold or hot environment (beyond the range of 104°F to -20°F) may trigger the auto turn off to protect the internal circuit.
- 6. Charging this speaker in a high temperature environment may trigger the auto turn off for charging to protect the battery. The Power Indicator will flash quickly to Indicate that the charging environmental temperature or the product Internal temperature is too high.
- 7. Recommended ambient storage temperature: -20°F-95°F RH <70% (recommended 77°C ±5°).

# FAQ

- Q: What kind of charger should we use for the speaker?
- A: While all common USB-C chargers can be used, we suggest 5V/2A or
- Q: What if there is noise or discontinuous sound during playback?
- A: Nomial range of the bluetooth speaker is 30ft with a clear unobstructed path. Please check if the speaker is within range with a clear path.
- Q: Wity did the speaker power off automatically without the Bluetooth
- discurrenting? A: If the speaker is not paired for longer than 10 min, it will automatically turn off
- Q: Why does the speaker not connect to the once-paired phone or device?

  A: Remove BT-200 from your Bluetooth Device List then restart pairing (pg 1-3).
- Q: What is the start up mode of the speaker?
- A: Default mode is Bluetooth
- Q: Wity will the speaker not power up?
- A: Plug in the charger and reby in a few minutes or by to long press the power button for 10-30 seconds to force reset.

### IMPORTANT SAFETY INSTRUCTIONS:

- 1. Do not personally disassemble or repair this speaker, otherwise it may cause product damage or personal injury
- 2. Do not use the speaker in dusty, humid, dry, or high-temperature environment.
- 3. Do not place this speaker near a heat source, in direct sunlight, in a dusty area or on vibrating surface.
- 4. In order to reduce the risk of fire, please do not cover this speaker while in use (newspapers, tablecloths, curtains etc.,).
- 5. This speaker is rated IPX7, please do not exceed the nominal parameters (submerged up to 1 meter of water for 30 minutes).
- 6. When any part of the product is damaged, such as the power cord, plug, liquid entering into or an object falling onto the device, and is unable to operate normally or fails, it must be repaired.
- 7. When the product is fully charged, do not keep the charger connected for a long period of time.
- 8. The maximum ambient temperature should not exceed 140°F.

"This speaker supports mobile phones and tablet PCs etc.

8

RoHS (E FC & X Made in China

powerbyss:::

5